

## ML JUNIOR

## 4G LTE INTERCOM SPECIFICATION

### FEATURES AND BENEFITS



- 316 marine grade stainless steel faceplate
- High strength, alloy cast back box
- LED downlight
- 40mm low profile backbox
- Stainless steel security screws
- Surface or flush mounted\*
- Downward facing microphone
- **THS** Horwood quality sound
- Call up to 8 numbers from each call point
- 10 to 99 users
- 7 programmable colours
- IP64 rated
- Time clock with 9 profiles
- 2 year warranty
- Backlit, vandal resistant keypad
- Timed trade button and clear button
- 400 pin codes for coded entry

H 224 x W 96 x D 40

\*Stainless Steel Only

### DOWNLOAD THE 'COMMTEL COMMAND ONE' APP



- Please pay particular attention to the Safety Message Contents included on the App front page (*View Safety Message*).

**OPEN | HOLD | CLOSE  
AT THE CLICK OF A BUTTON**

[www.telguard.co.uk/support/downloads/apps.html](http://www.telguard.co.uk/support/downloads/apps.html)

### EASY TO USE

- Multi-call point units such as the Junior generate the call destination by selecting the property number followed by the call button. Each call point destination has up to 8 cascading landline or mobile telephone numbers available. Once answered, if the recipient wants to grant access to the visitor they simply press the # key on their phone.

### DOWNLOADABLE ACTIVITY LOGS

- Download the last 10,000 interactions with the unit and see who is gaining entry, how and when. A great security feature for free.

### DIAL TO OPEN

- Authorise up to 900 numbers the ability to call the unit and open your door/gate. A modern and more cost effective alternative to traditional access control.

### EASY TO INSTALL

### TWO YEAR WARRANTY

### TECHNICAL SPECIFICATION

- **Power** 12 Volt 1 Amp. DC PSU fitted with a 3A fuse (*supplied and must be dedicated to the Telguard intercom unit*). Power Consumption: 120 mA Idle @ 12 Volts.
- **Telephone Type** Standard DTMF (*Dual Tone Multi Frequency*) generating telephone, cordless or mobile phone.
- **Programming** Remotely programmable via App, SMS or via GSM modem. Locally via USB cable. Hy-Can Link remotely and locally.
- **Relays** 3: 1 x 2A, 2 x 200mA, 2 x Auxiliary inputs.
- **Relay Activation Time** 1 ~ 60 seconds, adjustable locally and remotely.
- **Operating Commands** Default #, 2#, 3#, 4#, 5#, 6#, 7#, 8#, 9#. All relay commands are configurable.
- **Time Clocks** This utilizes the on board time clock enabling custom profile functions to be activated.
- **Authorised Call Access** 900 telephone numbers can be stored. Calling the unit, from an authorised telephone number activates the relay.



Raising Standards  
Safety Assured



EU CE Declaration of Conformity and Radio Equipment Directive is available at [www.commtel-uk.com](http://www.commtel-uk.com) | GB-RH10 9XN